

The Unitronics V130-33-R6 offers the following onboard I/Os:

- 8 Digital Inputs, configurable via wiring to include 2 Analog (current/voltage) and 1 HSC/Shaft-encoder Input
- 4 Analog Inputs (current)
- 6 Relay Outputs

I/O configurations can be expanded to include up to 256 I/Os via Expansion Modules. Available by separate order: Ethernet, additional RS232/RS485, CANbus.

You can find additional information, such as wiring diagrams, in the product's installation guide located on the Unitronics' Setup CD and in the Technical Library at [www.unitronics.com](http://www.unitronics.com).

### Technical Specifications

---

#### Power Supply

|                          |                                              |
|--------------------------|----------------------------------------------|
| Input voltage            | 24VDC                                        |
| Permissible range        | 20.4VDC to 28.8VDC with less than 10% ripple |
| Max. current consumption | See Note 1                                   |
| npn inputs               | 225mA@24VDC                                  |
| pnp inputs               | 165mA@24VDC                                  |

#### Notes:

1. To calculate the actual power consumption, subtract the current for each unused element from the maximum current consumption value according to the values below:

| <b>Backlight</b> | <b>Ethernet card</b> | <b>Relay Outputs<br/>(per output)</b> |
|------------------|----------------------|---------------------------------------|
| 10mA             | 35mA                 | 8mA                                   |

#### Digital Inputs

|                       |                                                                           |
|-----------------------|---------------------------------------------------------------------------|
| Number of inputs      | 8. See Note 2                                                             |
| Input type            | See Note 2                                                                |
| Galvanic isolation    | None                                                                      |
| Nominal input voltage | 24VDC                                                                     |
| Input voltage         |                                                                           |
| pnp (source)          | 0-5VDC for Logic '0'<br>17-28.8VDC for Logic '1'                          |
| npn (sink)            | 17-28.8VDC for Logic '0'<br>0-5VDC for Logic '1'                          |
| Input current         | 8mA@24VDC                                                                 |
| Input impedance       | 3KΩ                                                                       |
| Response time         | 10mS typical, when used as normal digital inputs                          |
| Input cable length    | Up to 100 meters, unshielded                                              |
| High speed inputs     | Specifications below apply when wired as HSC/shaft-encoder.<br>See Note 2 |
| Resolution            | 32-bit                                                                    |
| Frequency             | 10kHz maximum                                                             |
| Minimum pulse width   | 40μs                                                                      |

**Notes:**

2. This model comprises a total of 12 inputs. Input functionality can be adapted as follows:  
 8 inputs may be used as digital inputs. They may be wired, in a group, and set to either npn or pnp via a single jumper. 4 inputs may be used as analog inputs, current (AN2-AN5).  
 In addition, according to jumper settings and appropriate wiring:
- Inputs 6 and 7 can function as either digital or analog inputs.
  - Input 0 can function as a high-speed counter, as part of a shaft-encoder, or as a normal digital input.
  - Input 1 can function as either counter reset, as part of a shaft-encoder, or as a normal digital input.
  - If input 0 is set as a high-speed counter (without reset), input 1 can function as a normal digital input.

**Analog Inputs (current/voltage)**

|                            |                                                                                        |         |
|----------------------------|----------------------------------------------------------------------------------------|---------|
| Number of inputs           | 2, according to wiring as described above in Note 2                                    |         |
| Input type                 | Multi-range inputs: 0-10V, 0-20mA, 4-20mA                                              |         |
| Input range                | 0-20mA, 4-20mA                                                                         | 0-10VDC |
| Input impedance            | 243Ω                                                                                   | >150KΩ  |
| Maximum input rating       | 25mA, 6V                                                                               | 15V     |
| Galvanic isolation         | None                                                                                   |         |
| Conversion method          | Successive approximation                                                               |         |
| Resolution (except 4-20mA) | 10-bit (1024 units)                                                                    |         |
| Resolution (at 4-20mA)     | 204 to 1023 (820 units)                                                                |         |
| Conversion time            | One configured input is updated per scan. See Note 3                                   |         |
| Precision                  | 0.9%                                                                                   |         |
| Status indication          | Yes – if an analog input deviates above the permissible range, its value will be 1024. |         |

**Analog Inputs (current)**

|                            |                                                                                       |
|----------------------------|---------------------------------------------------------------------------------------|
| Number of inputs           | 4 (AN2-AN5)                                                                           |
| Input range                | 0-20mA, 4-20mA                                                                        |
| Input impedance            | 243Ω                                                                                  |
| Maximum input rating       | 25mA, 6V                                                                              |
| Galvanic isolation         | None                                                                                  |
| Conversion method          | Successive approximation                                                              |
| Resolution (except 4-20mA) | 10-bit (1024 units)                                                                   |
| Resolution (at 4-20mA)     | 204 to 1023 (820 units)                                                               |
| Conversion time            | One configured input is updated per scan. See Note 3                                  |
| Precision                  | 0.9%                                                                                  |
| Status indication          | Yes – if an analog input deviates above the permissible range, its value will be 1024 |

**Notes:**

3. For example, if 6 inputs are configured as analog, it takes 6 scans to update all analog values.

**Digital Outputs**

|                    |                                                                                                             |
|--------------------|-------------------------------------------------------------------------------------------------------------|
| Number of outputs  | 6 relay                                                                                                     |
| Output type        | SPST-NO (Form A)                                                                                            |
| Isolation          | By relay                                                                                                    |
| Type of relay      | Fujitsu, JY-24H-K or compatible                                                                             |
| Output current     | 5A maximum (resistive load)                                                                                 |
| Rated voltage      | 250VAC / 30VDC                                                                                              |
| Minimum load       | 10mA, 5VDC                                                                                                  |
| Life expectancy    | 50k operations at maximum load                                                                              |
| Response time      | 10mS (typical)                                                                                              |
| Contact protection | External precautions required (see <i>Increasing Contact Life Span</i> in the product's Installation Guide) |

**Graphic Display Screen**

|                        |                                                                                                 |
|------------------------|-------------------------------------------------------------------------------------------------|
| LCD Type               | STN, LCD display                                                                                |
| Illumination backlight | White LED, software-controlled                                                                  |
| Display resolution     | 128x64 pixels                                                                                   |
| Viewing area           | 2.4"                                                                                            |
| Screen contrast        | Via software (Store value to SI 7)<br>Refer to VisiLogic Help topic <i>Setting LCD Contrast</i> |

**Keypad**

|                |                                                                                                                                                                                                           |
|----------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Number of keys | 20 keys, including 10 user-labeled keys                                                                                                                                                                   |
| Key type       | Metal dome, sealed membrane switch                                                                                                                                                                        |
| Slides         | Slides may be installed in the operating panel faceplate to custom-label the keys and logo picture. A complete set of blank slides is available by separate order. Refer to <i>V130 Keypad Slides.pdf</i> |

**Program**

|                   |                                                                                                                                                                        |        |                        |
|-------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------|------------------------|
| Memory size       | Application Logic – 512kb, Images – 256 kb, Fonts – 128 kb                                                                                                             |        |                        |
| Operand type      | Quantity                                                                                                                                                               | Symbol | Value                  |
| Memory Bits       | 4096                                                                                                                                                                   | MB     | Bit (coil)             |
| Memory Integers   | 2048                                                                                                                                                                   | MI     | 16-bit signed/unsigned |
| Long Integers     | 256                                                                                                                                                                    | ML     | 32-bit signed/unsigned |
| Double Word       | 64                                                                                                                                                                     | DW     | 32-bit unsigned        |
| Memory Floats     | 24                                                                                                                                                                     | MF     | 32-bit signed/unsigned |
| Timers            | 192                                                                                                                                                                    | T      | 32-bit                 |
| Counters          | 24                                                                                                                                                                     | C      | 16-bit                 |
| Data Tables       | 120K dynamic data (recipe parameters, datalogs, etc.)<br>192K fixed data (read-only data, ingredient names, etc)<br>Expandable via SD card. See Removable Memory below |        |                        |
| HMI displays      | Up to 1024                                                                                                                                                             |        |                        |
| Program scan time | 20µS per 1kb of typical application                                                                                                                                    |        |                        |

**Removable Memory**

Micro SD card                      Compatible with fast SD cards of up to 2GB of memory; store datalogs, Alarms, Trends, Data Tables, backup Ladder, HMI, and OS.  
See Note 4

**Notes:**

4. User must format via Unitronics SD tools utility.

**Communication Ports**

|                    |                                                   |
|--------------------|---------------------------------------------------|
| Port 1             | 1 channel, RS232/RS485. See Note 5                |
| Galvanic isolation | No                                                |
| Baud rate          | 300 to 115200 bps                                 |
| RS232              |                                                   |
| Input voltage      | ±20VDC absolute maximum                           |
| Cable length       | 15m maximum (50')                                 |
| RS485              |                                                   |
| Input voltage      | -7 to +12VDC differential maximum                 |
| Cable type         | Shielded twisted pair, in compliance with EIA 485 |
| Cable length       | 1200m maximum (4000')                             |
| Nodes              | Up to 32                                          |
| Port 2 (optional)  | See Note 6                                        |
| CANbus (optional)  | See Note 6                                        |

**Notes:**

5. This model is supplied with a serial port: RS232/RS485 (Port 1). The standard is set to either RS232 or RS485 according to jumper settings. Refer to the product's Installation Guide.
6. The user may order and install one or both of the following modules:
  - An additional port (Port 2). Available port types: RS232/RS485 isolated/non-isolated, Ethernet.
  - A CANbus port.
 Port module documentation is available on the Unitronics website.

**I/O Expansion**

|        |                                                                                                                                                                                                         |
|--------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|        | Additional I/Os may be added. Configurations vary according to module. Supports digital, high-speed, analog, weight and temperature measurement I/Os.                                                   |
| Local  | Via I/O Expansion Port. Integrate up to 8 I/O Expansion Modules comprising up to 128 additional I/Os. Adapter required (P.N. EX-A1).                                                                    |
| Remote | Via CANbus port. Connect up to 60 adapters to a distance of 1000 meters from controller; and up to 8 I/O expansion modules to each adapter (up to a total of 256 I/Os). Adapter required (P.N. EX-RC1). |

**Miscellaneous**

|                     |                                                                                           |
|---------------------|-------------------------------------------------------------------------------------------|
| Clock (RTC)         | Real-time clock functions (date and time)                                                 |
| Battery back-up     | 7 years typical at 25°C, battery back-up for RTC and system data, including variable data |
| Battery replacement | Yes. Coin-type 3V, lithium battery, CR2450                                                |

**Dimensions**

|        |                                              |
|--------|----------------------------------------------|
| Size   | 109x114.1x68mm (4.29x4.49x2.67"). See Note 7 |
| Weight | 227g (8oz)                                   |

**Notes:**

7. For exact dimensions, refer to the product's Installation Guide.

**Environment**

|                         |                                                              |
|-------------------------|--------------------------------------------------------------|
| Operational temperature | 0 to 50°C (32 to 122°F)                                      |
| Storage temperature     | -20 to 60°C (-4 to 140°F)                                    |
| Relative Humidity (RH)  | 10% to 95% (non-condensing)                                  |
| Mounting method         | Panel mounted (IP65/NEMA4X)<br>DIN-rail mounted (IP20/NEMA1) |

The information in this document reflects products at the date of printing. Unitronics reserves the right, subject to all applicable laws, at any time, at its sole discretion, and without notice, to discontinue or change the features, designs, materials and other specifications of its products, and to either permanently or temporarily withdraw any of the forgoing from the market.

All information in this document is provided "as is" without warranty of any kind, either expressed or implied, including but not limited to any implied warranties of merchantability, fitness for a particular purpose, or non-infringement. Unitronics assumes no responsibility for errors or omissions in the information presented in this document. In no event shall Unitronics be liable for any special, incidental, indirect or consequential damages of any kind, or any damages whatsoever arising out of or in connection with the use or performance of this information.

The tradenames, trademarks, logos and service marks presented in this document, including their design, are the property of Unitronics (1989) (R<sup>G</sup>) Ltd. or other third parties and you are not permitted to use them without the prior written consent of Unitronics or such third party as may own them.