

This guide provides specifications for Unitronics model V350-35-R6. General features include: 8 Digital Inputs, including 2 Analog (current/voltage) and 1 HSC/Shaft-encoder, 4 Analog Inputs (current), 6 Relay Outputs, up to 512 I/Os via Expansion Modules, built-in RS232/RS485. Available by separate order: Ethernet, additional RS232/RS485, CANbus.

### Technical Specifications

---

#### Power Supply

Input voltage	24VDC
Permissible range	20.4VDC to 28.8VDC with less than 10% ripple
Max. current consumption	See Note 1
npn inputs	250mA@24VDC
pnp inputs	190mA@24VDC

#### Notes:

- To calculate the actual power consumption, subtract the current for each unused element from the maximum current consumption value according to the values below:

Backlight	Ethernet card	Relay Outputs (per output)
20mA	35mA	8mA

---

#### Digital Inputs

Number of inputs	8. See Note 2
Input type	See Note 2
Galvanic isolation	None
Nominal input voltage	24VDC
Input voltage	
pnp (source)	0-5VDC for Logic 0 17-28.8VDC for Logic 1
npn (sink)	17-28.8VDC for Logic 0 0-5VDC for Logic 1
Input current	8mA@24VDC
Input impedance	3K
Response time	10mSec typical, when used as normal digital inputs
Input cable length	Up to 100 meters, unshielded
High speed inputs	Specifications below apply when wired as HSC / shaft-encoder. See Note 2
Resolution	32-bit
Frequency	10kHz maximum
Minimum pulse width	40µs

**Notes:**

2. This model comprises a total of 12 inputs. Input functionality can be adapted as follows:  
 8 inputs may be used as digital inputs. They may be wired, in a group, and set to either npn or pnp via a single jumper. 4 inputs may be used as analog inputs, current (AN2-AN5).

In addition, according to jumper settings and appropriate wiring:

- Inputs 6 and 7 can function as either digital or analog inputs.
- Input 0 can function as a high-speed counter, as part of a shaft-encoder, or as a normal digital input.
- Input 1 can function as either counter reset, as part of a shaft-encoder, or as a normal digital input.
- If input 0 is set as a high-speed counter (without reset), input 1 can function as a normal digital input.

**Analog Inputs (current/voltage)**

Number of inputs	2, according to wiring as described above in Note 2	
Input type	Multi-range inputs: 0-10V, 0-20mA, 4-20mA	
Input range	0-20mA, 4-20mA	0-10VDC
Input impedance	243Ω	>150KΩ
Maximum input rating	25mA, 6V	15 V
Galvanic isolation	None	
Conversion method	Successive approximation	
Resolution (except 4-20mA)	10-bit (1024 units)	
Resolution (at 4-20mA)	204 to 1023 (820 units)	
Conversion time	Synchronized to cycle time	
Precision	0.9%	
Status indication	Yes – if an analog input deviates above the permissible range, its value will be 1024.	

**Analog Inputs (current)**

Number of inputs	4 (AN2-AN5)
Input range	0-20mA
Input impedance	243Ω
Maximum input rating	30mA
Galvanic isolation	None
Conversion method	Successive approximation
Resolution (except 4-20mA)	10-bit (1024 units)
Conversion time	20mSec, Synchronized to cycle time
Precision	±3.0%
Status indication	Yes – if an analog input deviates above the permissible range, its value will be 1024
Input cable length	Up to 10 meters, shielded twisted pair

**Digital Outputs**

Number of outputs	6 relay
Output type	SPST-NO (Form A)
Isolation	By relay
Type of relay	Fujitsu, JY-24H-K or compatible
Output current	5A maximum (resistive load)
Rated voltage	250VAC / 30VDC
Minimum load	10mA, 5VDC
Life expectancy	50k operations at maximum load
Response time	10mS (typical)
Contact protection	External precautions required (see <i>Increasing Contact Life Span</i> in the product's Installation Guide)

**Graphic Display Screen**

LCD Type	TFT, LCD display
Illumination backlight	White LED, software-controlled
Display resolution	320 x 240 pixels
Viewing area	3.5"
Colors	256
Touchscreen	Resistive, analog
'Touch' indication	Via buzzer
Screen brightness	Via software (Store value to SI 9)
Keypad	Displays virtual keyboard when the application requires data entry

**Keypad**

Number of keys	5 programmable function keys
Key type	Metal dome, sealed membrane switch
Slides	Slides may be installed in the operating panel faceplate to custom-label the keys. Refer to <i>V350 Keypad Slides.pdf</i> Two sets of slides are supplied with the controller: one set of arrow keys, and one blank set

**Program**

Memory size                      Application Logic – 1Mb, Images – 3Mb, Fonts – 512 Kb

Operand type	Quantity	Symbol	Value
Memory Bits	8192	MB	Bit (coil)
Memory Integers	4096	MI	16-bit signed/unsigned
Long Integers	512	ML	32-bit signed/unsigned
Double Word	256	DW	32-bit unsigned
Memory Floats	64	MF	32-bit signed/unsigned
Timers	384	T	32-bit
Counters	32	C	16-bit

Data Tables	120K dynamic data (recipe parameters, datalogs, etc.) 192K fixed data (read-only data, ingredient names, etc)
HMI displays	Up to 1024
Program scan time	15µS per 1kb of typical application

**Removable Memory**

Micro SD card

File system                      User must format via Unitronics SD tools utility. See Note 3

**Notes:**

- The micro SD memory card uses the PC-compatible FAT32 file system. User can store datalogs, Alarm history, Data Tables, backup Ladder, HMI, and OS, up to 2GB.

**Communication Ports**

Port 1                              1 channel, RS232/RS485. See Note 4

Galvanic isolation              No

Baud rate                         300 to 115200 bps

RS232

Input voltage                ±20VDC absolute maximum

Cable length                15m maximum (50')

RS485

Input voltage                -7 to +12VDC differential maximum

Cable type                    Shielded twisted pair, in compliance with EIA 485

Cable length                1200m maximum (4000')

Nodes                        Up to 32

Port 2 (optional)                See Note 5

CANbus (optional)              See Note 5

**Notes:**

- This model is supplied with a serial port: RS232/RS485 (Port 1). The standard is set to either RS232 or RS485 according to jumper settings. Refer to the product's Installation Guide.
- The user may order and install one or both of the following modules:
  - An additional port (Port 2). Available port types: RS232/RS485 isolated/non-isolated, Ethernet
  - A CANbus port
 Port module documentation is available on the Unitronics website.

**I/Os**

Via module                      Number of I/Os and types vary according to module. Supports up to 512 digital, high-speed, and analog I/Os.

    Expansion modules            Local adapter (P.N. EX-A1), via I/O Expansion Port. Integrate up to 8 I/O Expansion Modules comprising up to 128 additional I/Os.    Remote adapter (P.N. EX-RC1), via CANbus port. Connect up to 60 adapters; connect up to 8 I/O expansion modules to each adapter.**Miscellaneous**

Clock (RTC)                      Real-time clock functions (date and time).

Battery back-up                 7 years typical at 25°C, battery back-up for RTC and system data, including variable data

Battery replacement            Yes. Coin-type 3V, lithium battery, CR2450

**Dimensions**

Size	109 x 114.1 x 68mm (4.29 x 4.49 x 2.67"). See Note 6
Weight	227g (8 oz)

**Notes:**

6. For exact dimensions, refer to the product's Installation Guide.

---

**Environment**

Operational temperature	0 to 50°C (32 to 122°F)
Storage temperature	-20 to 60°C (-4 to 140°F)
Relative Humidity (RH)	10% to 95% (non-condensing)
Mounting method	Panel mounted (IP65/NEMA4X) DIN-rail mounted (IP20/NEMA1)

The information in this document reflects products at the date of printing. Unitronics reserves the right, subject to all applicable laws, at any time, at its sole discretion, and without notice, to discontinue or change the features, designs, materials and other specifications of its products, and to either permanently or temporarily withdraw any of the foregoing from the market.

All information in this document is provided "as is" without warranty of any kind, either expressed or implied, including but not limited to any implied warranties of merchantability, fitness for a particular purpose, or non-infringement. Unitronics assumes no responsibility for errors or omissions in the information presented in this document. In no event shall Unitronics be liable for any special, incidental, indirect or consequential damages of any kind, or any damages whatsoever arising out of or in connection with the use or performance of this information.

The tradenames, trademarks, logos and service marks presented in this document, including their design, are the property of Unitronics (1989) (R"G) Ltd. or other third parties and you are not permitted to use them without the prior written consent of Unitronics or such third party as may own them.

DTS-V350-R6 08/08